

Mini50

Bluetooth Wall-mounted Amplifier



Features

- Rated power: 2x20W /8Ω, 2x40W/4Ω
- Support wireless Bluetooth 5.0 and USB input
- 5 pre-set EQ mode available
- 1 AUX input and 1 AUX output for power extension
- With remote controller for convenient use
- Aluminum-alloy casing, small size and portable
- Power supply:DC12-24V/3-5A

Descriptions

Mini50 is a portable mixer amplifier with USB and Bluetooth, it has 1 Aux input and 1 Aux output for power extension, support 8Ω speaker output, what's more, it has small size but big power, it's 2 channels stereo speaker output, rated power is 2x60W. The device can meet the requirements of the users and can be widely applied in classroom, stores, Coffee shop and other small place.

Specifications

| Item | Mini50 |
|----------------------|------------------------------|
| Rated Power | 2×20W/2×40W |
| Impedance | 8Ω/4Ω |
| Freq. Resp. | 20Hz-32KHz |
| Distortion | ≤0.06%(1KHz/10W) |
| SNR | > 92dB |
| LINE IN Sensitivity | 0dB(1V) |
| LINE IN Impedance | 47KΩ |
| LINE Out Sensitivity | 2V(Max) |
| LINE Out Impedance | 47KΩ |
| BT Transmission | 10m |
| BT Standard | BT5.0 |
| Audio format | APT, FLAC, WAV, MP3, APE etc |
| Power Supply | DC12-24V/3-5A |
| Net Weight | 0.33KG |
| Gross Weight | 0.35KG |
| Product Dimension | 138mm ×55mm×136mm |